

PL06		PAR LED RGBWA/UV	DMX CHART		
6CH MODE	ATTRIBUTE	START	END	DESCRIPTION	
CH1	RED	0	255		
CH2	GREEN	0	255		
CH3	BLUE	0	255		
CH4	WHITE	0	255		
CH5	AMBER	0	255		
CH6	UV	0	255		

10CH MODE	ATTRIBUTE	START	END	DESCRIPTION	
CH1	DIMMER				
CH2	RED				
CH3	GREEN				
CH4	BLUE				
CH5	WHITE				
CH6	AMBER				
CH7	UV				
CH8	STROBE				
CH9	MACRO	0	62	NO FUNCTION	
		63	124	COLOR JUMP CHANGE	
		125	186	COLOR AUTO CHANGE	
		187	249	COLOR PULSE CHANGE	
		250	255	SOUND CONTROL	
CH10	MACRO SPEED				